

MULTIFUNCTION PROCESS CALIBRATOR

Model: 820

Pyrosales Part No: PIE-820

Technician Friendly operation

The unique and intuitive EZ-DIAL Double Click Menu makes it easier to setup then other multifunction calibrators

Use it as a milliamp and voltage calibrator

Source 0 to 24.00mA, 0 to 10.25V dc and -10.00 to 110.00mV. Read to 24.00mA, ± 60.00 V dc and -10.00 to 110.00mV; Simulate 2- wire transmitters

Calibrate directly in temperature with 0.1°C/°F resolution

Works with types J,K,T,E,R,S,B,N,G,C,D,L (J DIN), U (T DIN) and P (Platinel II), Pt 100 Ohm (3850,3902,3916,3926) & 1000 Ohm (3850); Copper 10 & 50 Ohm, Nickel 100 and 120 Ohm.

Easy to read

Ready to go right out of the box

Measure temperature sensors, frequency pickups, loop currents and voltage levels

Troubleshoot loop and wiring problems



CE Approved